


GW2208+

CAN FD/LIN gateway device



Scan the code to follow



- Network Integration with Protocol Bridging
- ECU Diagnostics with Advanced Calibration
- Comprehensive Data Logging and Analysis

Feature Overview

The GW2208+ is powerful gateway device capable of converting CAN/LIN bus data to Ethernet, supporting both online and offline modes (*offline gateway functionality to be supported in future updates.). It integrates advanced CAN/CAN FD and LIN bus technologies, supporting a wide range of communication protocols and flexible data processing capabilities. GW2208+ supports conversion between CAN and CAN FD, but also enables CAN-to-LIN and LIN-to-LIN communication, This allows GW2208+ to facilitate seamless communication across different bus protocols, greatly simplifying integration in complex networked systems.

GW2208+ is equipped with 8 CAN/CAN FD channels (125 kbps ~ 1 Mbps for CAN, up to 8 Mbps for CAN FD), 2 software-configurable LIN master/slave channels (0 ~ 20 kbps), and multiple digital I/O interfaces for versatile signal measurement and integration.

GW2208+ connects to a PC via Ethernet, ensuring high-speed data transmission and avoiding communication bottlenecks when processing large volumes of bus data. When paired with the powerful TSMaster software, the GW2208+ enables users to load and utilize database files in DBC, LDF, XML, and ARXML formats. It supports comprehensive monitoring, analysis, and simulation of bus traffic, and offers advanced functionalities such as UDS diagnostics, ECU flashing, CCP/XCP calibration.



Characteristics

- μ s (microsecond) level hardware message timestamps to meet advanced requirements
- Driver-free design for Windows
- 8 CAN/CAN FD channels, and 2 LIN channels
- Supports 2 digital output (DO) and 4 digital input (DI)
- Enables conversion between CAN, CAN FD, and LIN protocols
- Configurable CAN bit rate from 125 kbps to 1 Mbps; CAN FD supports up to 8 Mbps
- LIN protocol compliant with LIN 1.3/2.0/2.1/J2602, supporting 0~20 kbps baud rate
- LIN master/slave node configuration via software
- Software-configurable 120 Ω termination resistors for CAN channels
- Support Self-ACK mode for CAN
- Supports message filtering for CAN/CAN FD/LIN frames
- Bus relay and expansion capabilities
- Supports BLF and ASC data recording formats, with online/offline playback functionality
- Example project and API interfaces provided, simplifying secondary development
- Customizable conversion rules with persistent storage; offline gateway function (*to be supported in future updates)

Specification

| | |
|--------------------|--|
| Channel | 8 x CAN FD / 2 x LIN / 4 x DI / 2 x DO |
| PC Interface | RJ45 Ethernet |
| CAN Interface | Pluggable Terminal Block |
| LIN Interface | Pluggable Terminal Block |
| I/O Interface | Pluggable Terminal Block |
| Driver | Driver-free for Windows |
| CAN | Supports CAN 2.0 A and B protocols, compliant with the ISO 11898 1 standard, with baud rates from 125 Kbps to 1 Mbps |
| CAN FD | Supports CAN FD that complies with both ISO and non ISO standards, with baud rates from 125 Kbps to 8 Mbps |
| LIN | Supports LIN 1.3/2.0/2.1/J2602, with baud rates from 0 to 20 Kbps |
| FlexRay | FlexRay channel (A and B) |
| Cold Start | Supported |
| Timestamp Accuracy | 1 μ s, hardware message timestamp |
| Terminal Resistor | 120 Ω software-configurable termination for CAN channels |
| Isolation | DC 2500V isolation per CAN channel |

| | |
|-----------------------|-----------------------------------|
| Power Supply | DC power supply |
| Power Consumption | 5 W |
| Enclosure Material | Metal |
| Dimension | Approx. 105 x 83.70 x 45 mm |
| Weight | Approx. 300 g (net)/470 g (gross) |
| Operating Temperature | -40°C ~ 80°C |
| Operating Humidity | 10% ~ 90% RH (non-condensing) |
| Operating Environment | Avoid corrosive gases |

Ordering Information

| | | |
|----------------|---------|---------------------------|
| Network Device | GW2208+ | CAN FD/LIN gateway device |
|----------------|---------|---------------------------|

Shipping list

- GW2208+ device
- Category 6 Gigabit Ethernet cable

Pin definition

10-pin pluggable connector for CAN FD 1-4

| | | | |
|-------|-----------|--------|------------|
| PIN 1 | CAN 4_Low | PIN 2 | CAN 4_High |
| PIN 3 | CAN 3_Low | PIN 4 | CAN 3_High |
| PIN 5 | GND | PIN 6 | Shield |
| PIN 7 | CAN 2_Low | PIN 8 | CAN 2_High |
| PIN 9 | CAN 1_Low | PIN 10 | CAN 1_High |

12-pin pluggable connector (LIN, DIDO)

| | | | |
|--------|----------|--------|----------|
| PIN 1 | DO2 | PIN 2 | DO 1 |
| PIN 3 | COM_DO 2 | PIN 4 | COM_DO 1 |
| PIN 5 | DI 3 | PIN 6 | DI 4 |
| PIN 7 | DI 1 | PIN 8 | DI 2 |
| PIN 9 | LIN 1 | PIN 10 | LIN 2 |
| PIN 11 | CGND | PIN 12 | EXT_VCC |

10-pin pluggable connector for CAN FD 5-8

| | | | |
|-------|-----------|--------|------------|
| PIN 1 | CAN 8_Low | PIN 2 | CAN 8_High |
| PIN 3 | CAN 7_Low | PIN 4 | CAN 7_High |
| PIN 5 | CGND | PIN 6 | Shield |
| PIN 7 | CAN 6_Low | PIN 8 | CAN 6_High |
| PIN 9 | CAN 5_Low | PIN 10 | CAN 5_High |

